

# LED E26 Screw-In Bulb

E26 Base



## Specifications

<b>Bulb Type</b>	LED A19
<b>Base</b>	E26
<b>Color</b>	2700K, 3000K, 3500K, 4000K, 5000K
<b>CRI</b>	>80
<b>Beam Angle</b>	360°
<b>Input Voltage</b>	AC120V
<b>Wattage</b>	8W
<b>Lumen</b>	8W @ 800lm
<b>Operating Temp.</b>	-20°F to 120°F
<b>Rated Life</b>	15,000 hours
<b>Warranty</b>	2 year warranty

## Features

- Dimmable
- Same look-and-feel of an incandescent bulb
- Driver-less technology
- Rated for enclosed fixtures
- Energy efficient
- Cost-effective
- 2-year warranty

### Product Compliance & Certifications:

- UL

## Description

The first LED screw-in bulb looks exactly like the incandescent bulb. There is no dark zone on the base of the bulb and the light shines below the base. Nobody will steal it. The most cost-effective direct replacement of 60W incandescent bulb with 8W A19 LED screw-in. Start the saving now.

## Dimensions

**A19** 2.36" in diameter, 4.25" in height

### Before



The traditional A19 LED lamp has a hard cutoff of light at the dark base zone.

### After



The Aledra A19 bulb doesn't have a dark zone at the base and puts out light beyond the base.

## Ordering Information

Product Model	Wattage	Color	Replacing
AAL-7.7WA19-E26-30K	8W	3000K	60W
AAL-7.7WA19-E26-40K	8W	4000K	60W

\*Other colors are available made-to-order

**aledra**

425.430.4555 | info@aledra.com | sales@aledra.com | www.aledra.com